



Phantom Pack Phantom Power Supply 48V

Key Features:

- 2-channel 48V phantom power supply
- Output with very low ripple and background noise output
- Rugged metal housing
- Universal AC operating voltage (100 - 250VAC, 50 - 60Hz)

Overview:

Designed for professional recording, the Marantz Phantom Pack provides two independent channels of 48VDC phantom power. Its sophisticated circuitry delivers an extremely low-noise output, with virtually no intrusive power supply "ripple," ensuring that your recordings are crystal clean and true-to-life. With a rugged metal housing, compact dimensions and light weight (only about three pounds), the Phantom Pack is both perfect for the studio and compact and convenient for the road.

Specifications:

- DC output: 48 \pm 2VDC
- Current output: Max 6.5mA (short circuit) per channel
- Channel separation: >98dB
- Undulatory Voltage: < 0.15 mV
- Operating voltage: 100 - 240VAC, 50-60Hz
- Power consumption: 2.5W
- Dimensions: 6.3 x 5.1 x 2.2" (160 x 130 x 55mm)
- Weight: 3.0 lbs (1.4kg)